

Δ Bd.#	Part No.	Bd.	Sch. Ref.	Description	PAD	Price
	CPB1614			Main PCB "93" REV. E8	F	3.15
001	CPR0050	A1	J	0Ω, Jumper Wire	F	0.01
002	CPS1804	B1	EE2	8 Cond. Straight Header	F	0.19
003	CPR0050	C1	FF4	0Ω Jumper Wire	F	0.01
004	CPR0006	C1	FF1	510Ω ±5%, 1/4W, CF	F	0.01
005	CPR0029	C1	NN5	200KΩ ±5%, 1/4W, CF	F	0.01
006	CPR0006	C1	CC2	510Ω ±5%, 1/4W, CF	F	0.01
008	CPQ1310	B1	NN5	.1A, 300V, PNP, 2SA1371AE	F	0.23
009	CPR0140	B1	LL7	3.92KΩ ±1%, 1/4W, MF	F	0.01
010	CPC1058	A1	LL7	.1uF ±5%, 50V, Film	F	0.05
011	CPR0018	A1	MM4	62KΩ ±5%, 1/4W, CF	F	0.01
012	CPR0009	A1	EE5	1KΩ ±5%, 1/4W, CF	F	0.01
014	CPC1101	A2	FF5	10uF, 50V, Electrolytic	F	0.03
015	CPR0050	B2	J	0Ω, Jumper Wire	F	0.01
016	CPC1101	B1	EE4	10uF, 50V, Electrolytic	F	0.03
017	CPR0015	B1	NN4	22KΩ ±5%, 1/4W, CF	F	0.01
018	CPD1251	B1	FF5	10mA, 75V Diode, 1N4148	F	0.01
019	CPR0050	C1	NN4	0Ω, Jumper Wire	F	0.01
020	CPR0145	C2	FF5	15.8KΩ ±1%, 1/4W, MF	F	0.01
021	CPR0006	C2	MM3	510Ω ±5%, 1/4W, CF	F	0.01
022	CPR0143	C2	MM3	10.0KΩ ±1%, 1/4W, MF	F	0.01
023	CPR0143	C2	MM4	10.0KΩ ±1%, 1/4W, MF	F	0.01
026	CPC1102	C2	NN4	100uF, 25V, Electrolytic	F	0.04
029	CPR0143	C2	MM5	10.0KΩ ±1%, 1/4W, MF	F	0.01
030	CPR0144	C2	NN7	12.1KΩ ±1%, 1/4W, MF	F	0.01
031	CPR0143	C2	NN5	10.0KΩ ±1%, 1/4W, MF	F	0.01
032	CPR0050	C2	J	0Ω, Jumper Wire	F	0.01
033	CPI1405	B2	MM6	Quad OP Amp IC, LM324	F	0.24
034	CPR0144	B2	MM4	12.1KΩ ±1%, 1/4W, MF	F	0.01
035	CPC1102	C1	NN4	100uF, 25V, Electrolytic	F	0.04
036	CPQ1302	A2	FF5	30V, .3A, PNP, D, MPSA64	F	0.06
037	CPR0145	A2	MM4	15.8KΩ ±1%, 1/4W, MF	F	0.01
038	CPR0143	A2	MM6	10.0KΩ ±1%, 1/4W, MF	F	0.01
039	CPR0050	A2	FF4	0Ω, Jumper Wire	F	0.01
040	CPR0029	A2	MM6	200KΩ ±5%, 1/4W, CF	F	0.01
041	CPR0145	A2	NN7	15.8KΩ ±1%, 1/4W, MF	F	0.01
042	CPR0024	B2	NN7	3.3KΩ ±5%, 1/4W, CF	F	0.01
043	CPR0016	A3	LL8	33KΩ ±5%, 1/4W, CF	F	0.01
044	CPR0018	A3	MM7	62KΩ ±5%, 1/4W, CF	F	0.01
045	CPR0144	A3	LL8	12.1KΩ ±1%, 1/4W, MF	F	0.01
047	CPC1032	B3	MM8	.01uF ±5%, 50V, Film	F	0.03
048	CPR0050	A3	J	0Ω, Jumper Wire	F	0.01
049	CPI1414	B3	MM8	OP Amp / Comp. IC, LM392	F	0.57
050	CPR0024	B3	NN6	3.3KΩ ±5%, 1/4W, CF	F	0.01
051	CPR0143	B2	NN5	10.0KΩ ±1%, 1/4W, MF	F	0.01
052	CPR0024	B2	NN7	3.3KΩ ±5%, 1/4W, CF	F	0.01
053	CPR0024	B3	NN6	3.3KΩ ±5%, 1/4W, CF	F	0.01
054	CPC1032	B3	MM7	.01uF ±5%, 50V, Film	F	0.03
055	CPR0143	B3	MM8	10.0KΩ ±1%, 1/4W, MF	F	0.01
056	CPR0013	B3	NN8	6.8KΩ ±5%, 1/4W, CF	F	0.01
057	CPC1035	B3	NN8	3,300pF ±5%, 100V, Film	F	0.08
058	CPR0154	B3	MM8	44.2KΩ ±1%, 1/4W, MF	F	0.01
060	CPR0012	B3	NN8	2.7KΩ ±5%, 1/4W, CF	F	0.01
061	CPC1102	B3	LL8	100uF, 25V, Electrolytic	F	0.04
062	CPR0009	A3	EE3	1KΩ ±5%, 1/4W, CF	F	0.01
063	CPR0002	A3	FF5	18Ω ±5%, 1/4W, CF	F	0.01
064	CPR0126	A3	BB5	909Ω ±1%, 1/4W, MF	F	0.01
065	CPR0009	A3	EE6	1KΩ ±5%, 1/4W, CF	F	0.01
066	CPR0124	A3	EE6	75.0Ω ±1%, 1/4W, MF	F	0.01
067	CPR0050	A4	EE3	0Ω, Jumper Wire	F	0.01
068	CPR0050	A4	J	0Ω, Jumper Wire	F	0.01
071	CPQ1322	B3	EE5	30V, .6A, NPN, PN2222A, Motorola.	F	0.05

Δ Bd.#	Part No.	Bd.	Sch. Ref.	Description	PAD	Price	
	072	CPQ1322	B3	AA4	30V, .6A, NPN, PN2222A, Motorola.	F	0.05
	076	CPR0006	B4	CC5	510Ω ±5%, 1/4W, CF	F	0.01
	078	CPR0138	B3	BB4	2.15KΩ ±1%, 1/4W, MF	F	0.01
	080	CPD1253	B3	BB4	1A, 600V, Fast D., 1N4937	F	0.02
	081	CPC1040	B3	BB4	.015uF ±10%, 250V, Film	F	0.06
	082	CPC1041	B3	LL6	.33uF ±5%, 50V, Film	F	0.08
	083	CPR0050	C3	J	0Ω, Jumper Wire	F	0.01
	084	CPD1250	C3	AA5	100mA, 200V Diode, FDH400	F	0.02
	085	CPR0155	C3	DD1	68.1KΩ ±1%, 1/4W, MF	F	0.01
	086	CPD1250	C3	AA5	100mA, 200V Diode, FDH400	F	0.02
	087	CPR0157	C3	DD2	127KΩ ±1%, 1/4W, MF	F	0.01
	088	CPR0050	C3	BB1	0Ω, Jumper Wire	F	0.01
	089	CPC1102	C3	DD2	100uF, 25V, Electrolytic	F	0.04
	090	CPD1252	C3	DD1	1A, 1KV Diode, 1N4007	F	0.01
	092	CPR0050	C3	PP0	0Ω Jumper Wire	F	0.01
	092A	CPR0050	C3	PP0	0Ω Jumper Wire	F	0.01
	093	CPR0004	C3	CC4	270Ω ±5%, 1/4W, CF	F	0.01
	094	CPR0050	C3	NN8	0Ω, Jumper Wire	F	0.01
	095	CPR0143	C3	MM8	10.0KΩ ±1%, 1/4W, MF	F	0.01
	096	CPR0163	C3	NN7	28.0KΩ ±1%, 1/4W, MF	F	0.01
	097	CPR0155	C3	MM7	68.1KΩ ±1%, 1/4W, MF	F	0.01
	098	CPR0018	D2	BB1	62KΩ ±5%, 1/4W, CF	F	0.01
	099	CPR0013	D2	BB1	6.8KΩ ±5%, 1/4W, CF	F	0.01
	100A	CPR0050	D2	BB2	0Ω Jumper, pins 5 to 10.	F	0.01
	100B	CPQ1303	D3	BB2	30V, .6A, NPN, PN2222A	F	0.04
!	102	CPC1035	D2	HH8	3,300pF ±5%, 100V, Film	F	0.08
	104	CPC1000	D2	HH7	56pF ±5%, 100V, Ceramic	F	0.01
	106	CPR0168	D2	GG8	8.06KΩ ±1%, 1/4W, MF	F	0.01
	107	CPC1000	D2	HH7	56pF ±5%, 100V, Ceramic	F	0.01
	108	CPC1035	D2	HH7	3,300pF ±5%, 100V, Film	F	0.08
	109	CPR0029	E2	MM5	200KΩ ±5%, 1/4W, CF	F	0.01
	110	CPC1005	D1	HH6	1,000pF ±10%, 500V, Ceramic	F	0.01
!	111	CPR0501	E1	JJ9	"J" PRA Power Supply	F	0.79
	112	CPQ1310	D1	HH6	.1A, 300V, PNP, 2SA1371AE	F	0.23
	113	CPR0019	D1	HH6	100KΩ ±5%, 1/4W, CF	F	0.01
	114	CPR0050	E1	HH8	0Ω, Jumper Wire	F	0.01
	114A	CPR0050	D1	HH6	0Ω, Jumper Wire	F	0.01
!	115	CPI1403	E2	II7	PS Control IC, XRC5184	F	3.33
	116	CPD1252	E2	JJ9	1A, 1N4007	F	0.01
	117	CPR0050	E3	J	0Ω, Jumper Wire	F	0.01
	118	CPC1102	E2	II5	100uF, 25V, Electrolytic	F	0.04
	120	CPC1102	E2	II5	100uF, 25V, Electrolytic	F	0.04
	121	CPD1253	F2	II6	1A, 600V, Fast D., 1N4937	F	0.02
	122	CPD1253	F2	II6	1A, 600V, Fast D., 1N4937	F	0.02
	123	CPC1002	F2	HH9	330pF ±10%, 500V, Ceramic	F	0.01
	124	CPC1058	E2	JJ7	.1uF ±5%, 50V, Film	F	0.05
!	125	CPC1035	F2	KK7	3,300pF ±5%, 100V, Film	F	0.08
!	126	CPR0156	E2	KK7	93.1KΩ ±1%, 1/4W, MF	F	0.01
	127	CPQ1302	E2	JJ9	30V, .3A, PNP, D, MPSA64	F	0.06
	128	CPC1103	E2	HH9	220uF, 50V, Electrolytic	F	0.14
	129	CPC1009	G1	KK9	100pF ±10%, 500V, Ceramic	F	0.01
	130	CPD1251	F2	KK7	10mA, 75V Diode, 1N4148	F	0.01
	131	CPC1003	E1	JJ9	2,200pF ±20%, 1KV, Ceramic	F	0.02
	132	CPR0050	F1	JJ6	0Ω, Jumper Wire	F	0.01
	133	CPR0002	E1	JJ8	18Ω ±5%, 1/4W, CF	F	0.01
	134	CPR0147	F1	JJ7	1.00MΩ ±1%, 1/4W, MF	F	0.01
	135	CPM2123	F2	KK8	Heat Sink For P.S. FET.	F	0.16
!	136	CPQ1304	F2	KK8	4.5A, 450V, Mos Fet, 2SK1446LS	F	1.19
	136A	CPR0050	F2	KK8	22 Gage Buss Wire under P/S	F	0.01
	137	CPR0389	F1	KK8	.33Ω ±5%, 2W, MO	F	0.03
	138	CPC1006	G1	KK8	200pF ±10%, 1KV, Ceramic	F	0.01
	139	CPR0033	G1	JJ6	30Ω ±5%, 1/4W, CF	F	0.01

Δ	Bd.#	Part No.	Bd.	Sch. Ref.	Description	PAD	Price
	140	CPR0350	F1	KK8	47Ω ±10%, 1/2W, CC	F	0.06
	141	CPD1253	G1	JJ6	1A, 600V, Fast D., 1N4937	F	0.02
!	142	CPD1264	H1	KK6	2A, 600V Fast D., FR205-F	F	0.03
	143A	CPR0018	H1	HH8	62KΩ ±5%, 1/4W, CF	F	0.01
	143B	CPR0017	H1	HH8	36KΩ ±5%, 1/4W, CF	F	0.01
!	144	CPC1111	I1	GG8	220uF, 2=0V, Electrolytic	F	0.97
	145	CPS1753	J1	GG9	2 Cond. Right Angle Header	F	0.13
	145A	CPM2003	J1		Cable Tie, 4"	F	0.01
!	146	CPR0425	J2	GG9	3 Amp Slow Blo	F	0.32
!	148	CPD1264	J2	GG7	2A, 600V Fast D., FR205-F	F	0.03
	150	CPC1003	J2	GG7	2,200pF ±20%, 1KV, Ceramic	F	0.02
	152	CPR0050	I2	GG8	0Ω Jumper, CS=.40"	F	0.01
	155	CPC1003	J2	GG8	2,200pF ±20%, 1KV, Ceramic	F	0.02
!	156	CPD1264	J2	GG9	2A, 600V Fast D., FR205-F	F	0.03
	158	CPR0434	J3	FF9	Posistur 230V, 14Ω	F	0.51
!	159	CPR0426	J3	FF9	Inrush Current Limit	F	0.20
	161	CPS1758	I3	FF9	.093" Dia. Bead Pin, CC1	F	0.02
	162	CPS1758	I3	FF9	.093" Dia. Bead Pin, CC2	F	0.02
	162A	CPS1758	I3	EE9	.093" Dia. Bead Pin, CC3	F	0.02
!	163	CPC1111	I2	GG8	220uF, 250V, Electrolytic	F	0.97
	164	CPR0050	H2	J	0Ω, Jumper Wire	F	0.01
	165	CPR0050	H2	J	0Ω, Jumper Wire	F	0.01
	165A	CPR0050	H2	J	0Ω, Jumper Wire	F	0.01
!	166	CPT1559	H2	KK6	1793 S. M. Power Inductor	F	3.15
	167	CPD1253	G3	JJ6	1A, 600V, Fast D., 1N4937	F	0.02
	167A	CPR0018	H2	II4	62KΩ ±5%, 1/4W, CF	F	0.01
	168	CPD1253	G3	KK6	1A, 600V, Fast D., 1N4937	F	0.02
	169	CPD1253	G2	KK5	1A, 600V, Fast D., 1N4937	F	0.02
	170	CPD1253	G2	KK5	1A, 600V, Fast D., 1N4937	F	0.02
	171	CPC1104	F3	JJ6	1,000uF, 35V, Electrolytic	F	0.22
	172	CPR0050	G3	J	0Ω, Jumper Wire	F	0.01
	173	CPR0019	G3	HH4	100KΩ ±5%, 1/4W, CF	F	0.01
!	175	CPC1111	H3	II6	220uF, 250V, Electrolytic	F	0.97
	176	CPR0050	H4	LL9	0Ω, Jumper Wire	F	0.01
	177	CPR0050	H4	LL9	0Ω, Jumper Wire	F	0.01
	178	CPR0050	H4	J	0Ω, Jumper Wire	F	0.01
	180	CPR0432	G4	GG6	100KΩ @25°C Thermistor	F	0.18
	181	CPD1256	G3	HH6	3W, 160V Zener, BZT03-D160	F	0.22
	182	CPC1112	G3	JJ5	220uF, 100V, Electrolytic	F	0.33
	183	CPR0050	G3	J	0Ω, Jumper Wire	F	0.01
	184	CPR0050	G3	J	0Ω, Jumper Wire	F	0.01
	185	CPR0003	G3	NN3	4.7Ω ±5%, 1/4W, CF	F	0.01
	186	CPR0050	G3	J	0Ω, Jumper Wire	F	0.01
	187	CPR0050	F4	J	0Ω, Jumper Wire	F	0.01
	188	CPR0050	F3	OO3	0Ω, Jumper Wire	F	0.01
	189	CPR0015	F3	NN3	22KΩ ±5%, 1/4W, CF	F	0.01
	190	CPR0050	F3	J	0Ω, Jumper Wire	F	0.01
	191	CPR0050	F3	NN3	0Ω, Jumper Wire	F	0.01
	192	CPR0050	F3	MM3	0Ω, Jumper Wire	F	0.01
	193	CPR0050	E3	MM3	0Ω, Jumper Wire	F	0.01
	194	CPR0050	E3	MM5	0Ω, Jumper Wire	F	0.01
	195	CPR0003	E3	NN3	4.7Ω ±5%, 1/4W, CF	F	0.01
	195A	CPR0050	E3	J	0Ω, Jumper Wire	F	0.01
	196	CPD1252	E3	II1	1A, 1KV Diode, 1N4007	F	0.01
	197	CPR0050	E3	LL0	0Ω Jumper, 0.600" Long.	F	0.01
	198A	CPR0050	D3	JJ5	0Ω, Jumper Wire	F	0.01
	200	CPR0050	D3	J	0Ω, Jumper Wire	F	0.01
	202	CPR0050	D3	FF3	0Ω, Jumper Wire	F	0.01
	203	CPR0050	D3	FF1	0Ω, Jumper Wire	F	0.01
	204	CPR0050	D3	J	0Ω, Jumper Wire	F	0.01
	205	CPD1253	D3	FF4	1A, 600V, Fast D., 1N4937	F	0.02
	206	CPS1757	C4	CC1	12 Cond. Straight Header	F	0.25

Δ	Bd.#	Part No.	Bd.	Sch. Ref.	Description	PAD	Price
	207	CPC1036	D4	CC4	.047uF ±5%, 50V, Film	F	0.04
	208	CPR0009	D4	CC3	1KΩ ±5%, 1/4W, CF	F	0.01
	209	CPC1102	C4	DD2	100uF, 25V, Electrolytic	F	0.04
	210	CPI1410	C4	CC3	Dual Comp. IC, LM393N	F	0.17
	211	CPR0050	C4	CC3	0Ω, Jumper Wire	F	0.01
	212	CPQ1301	C4	AA3	60V, .6A, PNP, PN2907A	F	0.04
	213	CPD1250	B4	AA5	100mA, 200V Diode, FDH400	F	0.02
	214	CPR0050	C4	J	0Ω, Jumper Wire	F	0.01
	215	CPR0050	B4	J	0Ω, Jumper Wire	F	0.01
	216	CPR0050	B4	J	0Ω, Jumper Wire	F	0.01
	217	CPR0050	B4	J	0Ω, Jumper Wire	F	0.01
	218	CPR0050	B4	BB7	0Ω, Jumper Wire	F	0.01
	221	CPR0050	A4	DD7	0Ω, Jumper Wire	F	0.01
	222	CPR0050	A4	J	0Ω, Jumper Wire	F	0.01
	223	CPR0153	A4	BB7	20.0KΩ ±1%, 1/4W, MF	F	0.01
	225	CPR0000	A5	AA7	2.2Ω ±5%, 1/4W, CF	F	0.01
	226	CPR0124	A5	AA7	75.0Ω ±1%, 1/4W, MF	F	0.01
	228	CPR0050	A5	CC5	0Ω, Jumper Wire, CS=.30"	F	0.01
	231	CPR0153	A5	DD7	20.0KΩ ±1%, 1/4W, MF	F	0.01
	232	CPR0173	A5	CC7	64.9Ω ±1%, 1/4W, MF	F	0.01
	233	CPR0000	A5	CC7	2.2Ω ±5%, 1/4W, CF	F	0.01
	235	CPR0050	A5	BB7	0Ω, Jumper Wire	F	0.01
	236	CPR0050	A5	AA7	0Ω, Jumper Wire	F	0.01
	241	CPI1409	B5	BB6	Video Input IC, XRC5346A	F	2.47
	242	CPR0153	B4	CC7	20.0KΩ ±1%, 1/4W, MF	F	0.01
	243	CPR0003	B5	BB7	4.7Ω ±5%, 1/4W, CF	F	0.01
	244	CPR0122	B5	BB5	105Ω ±1%, 1/4W, MF	F	0.01
	245	CPR0132	C5	BB5	604Ω ±1%, 1/4W, MF	F	0.01
	246	CPR0029	C5	FF7	200KΩ ±5%, 1/4W, CF	F	0.01
	247	CPR0016	C5	FF8	33KΩ ±5%, 1/4W, CF	F	0.01
	248	CPR0011	C5	CC3	1.8KΩ ±5%, 1/4W, CF	F	0.01
	250	CPR0013	C5	CC3	6.8KΩ ±5%, 1/4W, CF	F	0.01
	251	CPR0013	C5	CC3	6.8KΩ ±5%, 1/4W, CF	F	0.01
	252	CPR0011	C5	CC4	1.8KΩ ±5%, 1/4W, CF	F	0.01
	253	CPD1251	D5	CC3	10mA, 75V Diode, 1N4148	F	0.01
	254	CPQ1303	C5	FF8	30V, .6A, NPN, PN2222A	F	0.04
	255	CPQ1303	C5	FF7	30V, .6A, NPN, PN2222A	F	0.04
	256	CPR0029	C5	FF8	200KΩ ±5%, 1/4W, CF	F	0.01
	257	CPR0019	C5	FF8	100KΩ ±5%, 1/4W, CF	F	0.01
	258	CPR0131	C5	BB5	464Ω ±1%, 1/4W, MF	F	0.01
	260	CPR0130	C5	BB5	412Ω ±1%, 1/4W, MF	F	0.01
	261	CPR0145	B5	BB5	15.8KΩ ±1%, 1/4W, MF	F	0.01
	264	CPR0152	B5	BB7	84.5Ω ±1%, 1/4W, MF	F	0.01
	266	CPR0050	B6	CC7	0Ω, Jumper Wire	F	0.01
	267	CPC1102	B5	DD6	100uF, 25V, Electrolytic	F	0.04
	268	CPD1251	B6	CC7	10mA, 75V Diode, 1N4148	F	0.01
	270	CPD1251	B6	BB7	10mA, 75V Diode, 1N4148	F	0.01
	271	CPD1251	B6	AA7	10mA, 75V Diode, 1N4148	F	0.01
	272	CPR0140	C5	DD7	3.92KΩ ±1%, 1/4W, MF	F	0.01
	273	CPR0130	C6	DD8	412Ω ±1%, 1/4W, MF	F	0.01
	274	CPQ1303	C6	DD7	30V, .6A, NPN, PN2222A	F	0.04
	275	CPR0033	C6	DD8	30Ω ±5%, 1/4W, CF	F	0.01
	276	CPR0124	B6	CC7	75.0Ω ±1%, 1/4W, MF	F	0.01
	277	CPR0124	B6	BB7	75.0Ω ±1%, 1/4W, MF	F	0.01
	278	CPR0124	B6	AA7	75.0Ω ±1%, 1/4W, MF	F	0.01
	280	CPR0050	B6	BB8	0Ω, Jumper Wire	F	0.01
	281	CPR0050	B6	AA8	0Ω, Jumper Wire	F	0.01
	283	CPR0050	B6	CC8	0Ω, Jumper Wire	F	0.01
	284	CPR0124	B6	CC9	75.0Ω ±1%, 1/4W, MF	F	0.01
	286	CPR0124	B6	BB9	75.0Ω ±1%, 1/4W, MF	F	0.01
	288	CPR0124	A6	AA9	75.0Ω ±1%, 1/4W, MF	F	0.01
	292	CPS1752	A6	BB9	7 Cond. Straight Header	F	0.18

Δ Bd.#	Part No.	Bd.	Sch. Ref.	Description	PAD	Price
	293	CPR0050	A6	DD5	0Ω, Jumper Wire	F 0.01
	295	CPR0050	A7	EE3	0Ω, Jumper Wire	F 0.01
	296	CPI1407	A7	EE3	12V, 1A, Regulator, 7812	F 0.25
	297	CPR0050	A7	J	0Ω, Jumper Wire	F 0.01
	298	CPC1103	A7	FF3	220uF, 50V, Electrolytic	F 0.14
	304	CPC1102	B7	EE3	100uF, 25V, Electrolytic	F 0.04
	314	CPR0050	C7	J	0Ω, Jumper Wire	F 0.01
	318	CPC1036	C6	FF8	.047uF ±5%, 50V, Film	F 0.04
	321	CPR0013	C7	EE8	6.8KΩ ±5%, 1/4W, CF	F 0.01
	322	CPR0013	C7	EE8	6.8KΩ ±5%, 1/4W, CF	F 0.01
	323	CPR0015	C7	EE8	22KΩ ±5%, 1/4W, CF	F 0.01
	324	CPR0050	C7	J	0Ω, Jumper Wire	F 0.01
	325	CPR0011	C7	DD8	1.8KΩ ±5%, 1/4W, CF	F 0.01
	326	CPR0004	D7	DD8	270Ω ±5%, 1/4W, CF	F 0.01
	327	CPR0004	D7	EE9	270Ω ±5%, 1/4W, CF	F 0.01
	328	CPR0050	D7	DD9	0Ω, Jumper Wire	F 0.01
	329	CPR0144	D6	EE4	12.1KΩ ±1%, 1/4W, MF	F 0.01
	330	CPR0004	D7	DD9	270Ω ±5%, 1/4W, CF	F 0.01
	331	CPR0011	D7	DD9	1.8KΩ ±5%, 1/4W, CF	F 0.01
!	332	CPT1505	E7	NN1	Horizontal Drive Transformer	F 0.72
	333	CPD1252	D6	FF3	1A, 1KV Diode, 1N4007	F 0.01
	334	CPC1103	E6	FF4	220uF, 50V, Electrolytic	F 0.14
	336	CPR0012	E6	KK4	2.7KΩ ±5%, 1/4W, CF	F 0.01
	337	CPQ1307	E7	MM1	1.5A, 180V, NPN, 2SC4159E	F 0.46
	338	CPC1102	E7	LL1	100uF, 25V, Electrolytic	F 0.04
	340	CPR0391	F7	LL1	200Ω ±5%, 2W, MO	F 0.03
	341	CPR0371	F7	LL0	1KΩ ±5%, 1/2W, CF	F 0.01
	342	CPD1252	F6	LL1	1A, 1KV Diode, 1N4007	F 0.01
	343	CPC1003	F6	MM1	2,200pF ±20%, 1KV, Ceramic	F 0.02
	344	CPC1100	E6	II4	1uF, 50V, Electrolytic	F 0.04
!	345	CPC1035	E6	JJ4	3,300pF ±5%, 100V, Film	F 0.08
	346	CPC1032	E6	JJ4	.01uF ±5%, 50V, Film	F 0.03
	347	CPC1100	E6	II4	1uF, 50V, Electrolytic	F 0.04
	348	CPC1035	E6	II4	3,300pF ±5%, 100V, Film	F 0.08
	350	CPC1025	D6	HH4	330pF ±5%, 50V, Film	F 0.06
	351	CPC1025	D6	GG4	330pF ±5%, 50V, Film	F 0.06
	352	CPC1000	D6	EE4	56pF ±5%, 100V, Ceramic	F 0.01
	353	CPR0145	D6	FF6	15.8KΩ ±1%, 1/4W, MF	F 0.01
	354	CPR0155	D6	GG6	68.1KΩ ±1%, 1/4W, MF	F 0.01
	355	CPI1406	C6	FF7	Quad Comparator IC, LM339	F 0.18
	356	CPR0012	C6	FF7	2.7KΩ ±5%, 1/4W, CF	F 0.01
	357	CPR0009	C6	GG6	1KΩ ±5%, 1/4W, CF	F 0.01
	358	CPC1035	C6	GG7	3,300pF ±5%, 100V, Film	F 0.08
	360	CPR0145	C6	GG6	15.8KΩ ±1%, 1/4W, MF	F 0.01
	361	CPR0157	D6	HH2	127KΩ ±1%, 1/4W, MF	F 0.01
	362	CPR0171	D6	HH2	365KΩ ±1%, 1/4W, MF	F 0.01
	363	CPR0034	D5	HH2	2.2MΩ ±5%, 1/4W, CF	F 0.01
	364	CPR0142	D5	EE6	7.15KΩ ±1%, 1/4W, MF	F 0.01
	365	CPR0050	C5	J	0Ω, Jumper Wire	F 0.01
	366	CPR0142	D5	EE6	7.15KΩ ±1%, 1/4W, MF	F 0.01
	367	CPR0002	D5	FF3	18Ω ±5%, 1/4W, CF	F 0.01
	368	CPR0011	D5	CC3	1.8KΩ ±5%, 1/4W, CF	F 0.01
	369	CPC1005	E4	FF1	1,000pF ±10%, 500V, Ceramic	F 0.01
	370	CPR0015	D5	JJ2	22KΩ ±5%, 1/4W, CF	F 0.01
	371	CPR0029	D5	JJ1	200KΩ ±5%, 1/4W, CF	F 0.01
	372	CPR0029	D5	KK1	200KΩ ±5%, 1/4W, CF	F 0.01
	373	CPQ1303	D5	KK1	30V, .6A, NPN, PN2222A	F 0.04
	374	CPC1032	D5	GG1	.01uF ±5%, 50V, Film	F 0.03
	375	CPR0156	D5	GG1	93.1KΩ ±1%, 1/4W, MF	F 0.01
	376	CPC1102	D4	FF3	100uF, 25V, Electrolytic	F 0.04
!	377	CPI1415	E4	GG0	V. Deflection IC, LA7838	F 1.31
	378	CPM2121	F4	FF0	LA7838 Heat Sink.	F 0.28

Δ Bd.#	Part No.	Bd.	Sch. Ref.	Description	PAD	Price
	378	CPM2122	F4	FF0	LA7838 Heat Sink.	F 0.30
	379	CPQ1303	E4	BB2	30V, .6A, NPN, PN2222A	F 0.04
	380	CPC1109	E4	II1	470uF, 50V, Electrolytic	F 0.34
	381A	CPC1035	D4	HH1	3,300pF ±5%, 100V, Film	F 0.08
	382	CPR0019	E4	HH1	100KΩ ±5%, 1/4W, CF	F 0.01
	383	CPR0029	E4	AA2	200KΩ ±5%, 1/4W, CF (CS=.45)	F 0.01
	384	CPR0015	E4	AA2	22KΩ ±5%, 1/4W, CF	F 0.01
	385	CPR0376	E4	HH2	1.2Ω ±5%, 1W, MO	F 0.02
	388	CPR0157	F4	HH2	127KΩ ±1%, 1/4W, MF	F 0.01
	389	CPR0050	E4	BB2	0Ω, Jumper Wire, CS=.74"	F 0.01
	390	CPR0019	F4	II1	100KΩ ±5%, 1/4W, CF	F 0.01
	391	CPC1043	F5	HH2	1uF ±5%, 50V, Film	F 0.16
	392	CPR0012	F5	HH1	2.7KΩ ±5%, 1/4W, CF	F 0.01
	393	CPR0155	E5	HH1	68.1KΩ ±1%, 1/4W, MF	F 0.01
	394	CPR0364	E5	NN3	100Ω ±5%, 1/2W, CF	F 0.01
	395	CPR0050	E5	II1	0Ω, Jumper Wire	F 0.01
	396	CPR0003	E5	JJ1	4.7Ω ±5%, 1/4W, CF	F 0.01
	397	CPC1037	E5	JJ1	.1uF ±5%, 250V, Film	F 0.07
	398	CPC1009	E4	II1	100pF ±10%, 500V, Ceramic	F 0.01
	400	CPR0050	E4	J	0Ω, Jumper Wire	F 0.01
	401	CPC1043	E5	HH1	1uF ±5%, 50V, Film	F 0.16
	402	CPR0163	E5	GG1	28.0KΩ ±1%, 1/4W, MF	F 0.01
	403	CPR0156	E5	GG2	93.1KΩ ±1%, 1/4W, MF	F 0.01
	405	CPD1251	E5	KK1	10mA, 75V Diode, 1N4148	F 0.01
	406	CPD1251	E5	JJ1	10mA, 75V Diode, 1N4148	F 0.01
	408	CPR0145	E5	JJ3	15.8KΩ ±1%, 1/4W, MF	F 0.01
	409	CPQ1301	D5	KK0	60V, .6A, PNP, PN2907A	F 0.04
	410	CPC1058	E5	GG2	.1uF ±5%, 50V, Film	F 0.05
	411	CPQ1303	D5	JJ1	30V, .6A, NPN, PN2222A	F 0.04
	412	CPR0029	D5	JJ0	200KΩ ±5%, 1/4W, CF	F 0.01
	413	CPR0029	D5	KK0	200KΩ ±5%, 1/4W, CF	F 0.01
	414	CPC1035	D6	II2	3,300pF ±5%, 100V, Film	F 0.08
!	415	CPI1400	E6	KK3	H. Control IC, LA7851	F 1.59
!	416	CPR0502	E6	II4	"I" PRA Horizontal Control	F 0.79
	417	CPR0140	E5	KK3	3.92KΩ ±1%, 1/4W, MF	F 0.01
	418	CPR0140	E5	KK2	3.92KΩ ±1%, 1/4W, MF	F 0.01
	419A	CPR0050	F5	OO2	0Ω, Jumper, Normal Vertical.	F 0.01
	419B	CPR0050	F6	OO2	0Ω, Jumper, Normal Vertical.	F 0.01
	420	CPQ1308	E5	NN3	.1A, 200V, NPN, 2SC3467AE	F 0.18
	421	CPR0393	F6	MM2	390Ω ±5%, 2W, MO	F 0.03
	422	CPR0050	F5	KK1	0Ω, Jumper Wire	F 0.01
	423	CPR0006	F5	OO3	510Ω ±5%, 1/4W, CF	F 0.01
	424	CPR0004	F5	OO3	270Ω ±5%, 1/4W, CF	F 0.01
	425	CPR0367	F5	OO3	150Ω ±5%, 1/2W, CF	F 0.01
	426	CPS1758	F5	OO2	.093" Dia. Bead Pin, YC1	F 0.02
	427	CPS1758	F5	OO2	.093" Dia. Bead Pin, YC2	F 0.02
	428	CPR0367	F6	OO6	150Ω ±5%, 1/2W, CF	F 0.01
	430	CPR0050	F6	OO6	0Ω, Jumper Wire	F 0.01
	431	CPT1557	F6	OO6	H. Linearity Inductor	F 0.77
	432	CPC1006	F6	OO6	200pF ±10%, 1KV, Ceramic	F 0.01
!	433	CPQ1318	G7	NN1	12A, 1.5KV, NPN, 2SC5690	F 3.45
	434	CPR0376	G7	NN1	1.2Ω ±5%, 1W, MO	F 0.02
	435	CPD1252	G7	NN1	1A, 1KV Diode, 1N4007	F 0.01
!	437	CPC1034	H7	PP7	.022uF ±3%, 630V, Film	F 0.08
	440	CPD1259	H6	PP6	3A, 1KV Fast Diode, TF307	F 0.12
!	441	CPC1030	H6	PP6	.01uF ±3%, 1.6KV, Film	F 0.24
!	443	CPC1050	H6	PP7	.47uF ±5%, 250V, Film	F 0.31
!	444	CPC1050	H6	OO7	.47uF ±5%, 250V, Film	F 0.31
	445	CPS1758	G5	PP5	.093" Dia. Bead Pin, YC4	F 0.02
	446	CPS1758	G5	OO5	.093" Dia. Bead Pin, YC3	F 0.02
	447	CPT1538	G5	PP3	12 mH, H. Raster Shift Inductor	F 0.74
	449	CPC1104	F4	MM2	1,000uF, 35V, Electrolytic	F 0.22

Δ Bd.#	Part No.	Bd. Sch. Ref.	Description	PAD	Price
450	CPC1104	G4 KK6	1,000uF, 35V, Electrolytic	F	0.22
452	CPR0050	G4 NN1	0Ω, Jumper Wire	F	0.01
! 453	CPT1555	H5 OO2	31KHz, .45mA, FBT Meritron CT-8819	F	13.13
454	CPR0050	I6 OO7	0Ω, Jumper Wire	F	0.01
456	CPC1044	I6 OO8	2.7uF ±10%, 100V, Film	F	0.37
457	CPT1560	I7 OO7	100uH Horz. Width Inductor	F	0.75
458	CPT1511	J7 OO7	50uH Control Inductor	F	0.70
460	CPQ1315	J6 OO8	8A, 100V, Mos Fet, IRF520	F	0.41
461	CPR0006	J6 NN8	510Ω ±5%, 1/4W, CF	F	0.01
462	CPD1253	J6 NN7	1A, 600V, Fast D., 1N4937	F	0.02
463	CPC1005	J6 OO8	1,000pF ±10%, 500V, Ceramic	F	0.01
464	CPR0365	J6 OO8	470Ω ±5%, 1/2W, CF	F	0.01
465	CPR0050	I6 PP1	0Ω, Jumper Wire	F	0.01
466	CPR0050	I6 MM2	0Ω, Jumper Wire	F	0.01
468	CPR0433	J5 EE9	24V coil, 200V @ .5A Relay	F	0.83
470	CPR0352	J6 EE9	470Ω ±10%, 1/2W, CC	F	0.06
473	CPR0050	G6 J	0Ω, Jumper Wire	F	0.01
475	CPR0374	H7 PP7	.10Ω ±5%, 1W, MO	F	
476	CPR0374	H7 PP7	.10Ω ±5%, 1W, MO	F	
477	CPD1266	H7 PP7	2A, 400V, Fast D., HER205	F	0.07
478	CPD1266	H7 PP7	2A, 400V, Fast D., HER205	F	0.07
480	CPR0050	G7 J	0Ω, Jumper Wire	F	0.01
481	CPR0402	EE1	10K ±20%, Yellow Pot	F	0.20
482	CPR0405	EE1	500Ω ±20%, Black Pot	F	0.20
483	CPR0401	EE1	1K ±20%, Blue Pot	F	0.20
484	CPR0403	EE2	20K ±20%, Orange Pot	F	0.20
485	CPR0400	EE2	1K ±20%, White Pot	F	0.20
486	CPR0007	FF1	750Ω ±5%, 1/4W, CF	F	0.01
490	CPB1603	YY0	Remote Control PCB	F	0.49
500	CPC1041	F4 NN4	.33uF ±5%, 50V, Film	F	0.08
501	CPR0009	G4 NN4	1KΩ ±5%, 1/4W, CF	F	0.01
502	CPR0050	G4 NN5	0Ω, Jumper Wire	F	0.01
503	CPR0158	G4 OO4	84.5KΩ ±1%, 1/4W, MF	F	0.01
504	CPR0147	G4 OO4	1.00MΩ ±1%, 1/4W, MF	F	0.01
505	CPR0017	G4 OO4	36KΩ ±5%, 1/4W, MF	F	0.01
507	CPC1003	G4 PP3	2,200pF ±20%, 1KV, Ceramic	F	0.02
508	CPR0050	G5 J	0Ω, Jumper Wire	F	0.01
509	CPQ1308	G4 OO4	.1A, 200V, NPN, 2SC3467AE	F	0.18
510	CPR0034	G5 OO4	2.2MΩ ±5%, 1/4W, CF	F	0.01
511	CPR0034	G5 OO4	2.2MΩ ±5%, 1/4W, CF	F	0.01
512	CPD1252	G5 PP4	1A, 1KV Diode, 1N4007	F	0.01
514	CPR0029	G5 OO4	200KΩ ±5%, 1/4W, CF	F	0.01
515	CPC1002	H5 PP4	330pF ±10%, 500V, Ceramic	F	0.01
516	CPR0004	H6 OO6	270Ω ±5%, 1/4W, CF	F	0.01
517	CPC1037	H6 OO5	.1uF ±5%, 250V, Film	F	0.07
518	CPT1556	I6 PP4	Dynamic Focus Transformer	F	0.86
520	CPR0352	J5 PP1	470Ω ±10%, 1/2W, CC	F	0.06
521	CPR0050	J4 J	0Ω, Jumper Wire	F	0.01
522	CPR0050	J4 J	0Ω, Jumper Wire	F	0.01
523	CPR0050	J4 J	0Ω, Jumper Wire	F	0.01
524	CPR0050	H4 PP2	0Ω, Jumper Wire	F	0.01
525	CPR0050	H4 PP2	0Ω, Jumper Wire	F	0.01
526	CPR0050	H4 J	0Ω, Jumper Wire	F	0.01
529	CPR0179	E1 GG6	392K ±1%, 1/4W, MF.	F	0.01
529A	CPR0050	F1 J	0Ω, Jumper Wire	F	0.01
531	CPR0050	F1 J	0Ω, Jumper Wire	F	0.01
533	CPR0050	G1 KK7	0Ω, Jumper Wire, CS=.450"	F	0.01
800	CPB1613	L4 YY0	Video Board PCB E7	F	0.89
801	CPC1058	P1 YY2	.1uF ±5%, 50V, Film	F	0.05
802	CPR0050	P1 J	0Ω, Jumper Wire	F	0.01
803	CPR0510	P1 RR2	"K" PRA Video Amplifier	F	1.02
804	CPR0050	P1 J	0Ω, Jumper Wire	F	0.01

Δ Bd.#	Part No.	Bd. Sch. Ref.	Description	PAD	Price
805	CPQ1308	P1 SS4	.1A, 200V, NPN, 2SC3467AE	F	0.18
806	CPR0050	P1 J	0Ω, Jumper Wire	F	0.01
807	CPR0050	N1 J	0Ω, Jumper Wire	F	0.01
808	CPR0050	P1 J	0Ω, Jumper Wire	F	0.01
810	CPQ1308	N1 SS1	.1A, 200V, NPN, 2SC3467AE	F	0.18
811	CPR0510	N1 RR0	"K" PRA Video Amplifier	F	1.02
812	CPQ1301	N2 SS2	60V, .6A, PNP, PN2907A	F	0.04
813	CPR0050	N2 J	0Ω, Jumper Wire	F	0.01
814	CPR0050	N2 J	0Ω, Jumper Wire	F	0.01
815	CPC1003	N2 VV5	2,200pF ±20%, 1KV, Ceramic	F	0.02
816	CPC1058	N2 YY2	.1uF ±5%, 50V, Film	F	0.05
817	CPC1058	N1 UU2	.1uF ±5%, 50V, Film	F	0.05
818	CPC1003	P2 VV5	2,200pF ±20%, 1KV, Ceramic	F	0.02
820	CPR0050	P2 J	0Ω, Jumper Wire	F	0.01
821	CPR0050	P2 J	0Ω, Jumper Wire	F	0.01
822	CPQ1301	P2 SS4	60V, .6A, PNP, PN2907A	F	0.04
823	CPC1037	P2 TT3	.1uF ±5%, 250V, Film	F	0.07
824	CPC1040	P2 SS3	.015uF ±10%, 250V, Film	F	0.06
825	CPR0127	P2 SS4	205Ω ±1%, 1/4W, MF	F	0.01
826	CPR0050	P2 J	0Ω, Jumper Wire	F	0.01
827	CPQ1301	P2 SS3	60V, .6A, PNP, PN2907A	F	0.04
828	CPQ1309	P2 SS3	.1A, 200V, PNP, 2SA1370AE	F	0.23
830	CPR0011	P2 TT4	1.8KΩ ±5%, 1/4W, CF	F	0.01
831	CPR0011	N2 TT2	1.8KΩ ±5%, 1/4W, CF	F	0.01
832	CPQ1301	N2 SS0	60V, .6A, PNP, PN2907A	F	0.04
833	CPQ1309	N2 SS0	.1A, 200V, PNP, 2SA1370AE	F	0.23
834	CPR0127	N2 SS1	205Ω ±1%, 1/4W, MF	F	0.01
835	CPD1250	N3 UU0	100mA, 200V Diode, FDH400	F	0.02
836	CPR0011	N3 TT1	1.8KΩ ±5%, 1/4W, CF	F	0.01
837	CPQ1309	N2 TT2	.1A, 200V, PNP, 2SA1370AE	F	0.23
838	CPC1005	N3 TT1	1,000pF ±10%, 500V, Ceramic	F	0.01
840	CPD1250	N3 TT1	100mA, 200V Diode, FDH400	F	0.02
841	CPD1250	P3 TT4	100mA, 200V Diode, FDH400	F	0.02
842	CPQ1309	P2 TT4	.1A, 200V, PNP, 2SA1370AE	F	0.23
843	CPC1005	P3 TT4	1,000pF ±10%, 500V, Ceramic	F	0.01
844	CPR0011	P3 TT4	1.8KΩ ±5%, 1/4W, CF	F	0.01
845	CPD1250	P3 VV0	100mA, 200V Diode, FDH400	F	0.02
846	CPC1043	P3 XX2	1uF ±5%, 50V, Film	F	0.16
847	CPD1253	P3 WW2	1A, 600V, Fast D., 1N4937	F	0.02
848	CPD1252	P3 WW2	1A, 1KV Diode, 1N4007	F	0.01
849	CPD1250	P3 VV0	100mA, 200V Diode, FDH400	F	0.02
850	CPQ1306	P3 ZZ3	.1A, 1.5KV, NPN, 2SC3675	F	0.88
851	CPR0365	N3 WW0	470Ω ±5%, 1/2W, CF	F	0.01
852	CPR0018	N3 ZZ3	62KΩ ±5%, 1/4W, CF	F	0.01
! 854	CPC1046	N3 XX1	.047uF ±5%, 200V, Film	F	0.32
855	CPR0371	N4 XX1	1KΩ ±5%, 1/2W, CF	F	0.01
856	CPR0366	N4 YY1	100KΩ ±5%, 1/2W, CF	F	0.01
! 857	CPC1052	N3 WW2	.018uF ±5%, 200V, Film	F	0.07
858	CPR0170	P3 YY3	294KΩ ±1%, 1/4W, MF	F	0.01
859	CPR0032	P4 YY2	30Ω ±5%, 1/4W, CF, Hairpin.	F	0.01
861	CPR0050	P3 J	0Ω, Jumper Wire	F	0.01
862	CPR0050	P4 J	0Ω, Jumper Wire	F	0.01
863	CPS1772	P4 ZZ3	12 Cond. Video Cable, 12"	F	1.24
864	CPR0050	P4 J	0Ω, Jumper Wire	F	0.01
865	CPR0050	P4 J	0Ω, Jumper Wire	F	0.01
866	CPR0009	N4 YY3	1KΩ ±5%, 1/4W, CF	F	0.01
867	CPR0050	N4 J	0Ω, Jumper Wire	F	0.01
868	CPC1101	N4 VV2	10uF, 50V, Electrolytic	F	0.03
869	CPR0050	M3 XX1	0Ω, Jumper Wire	F	0.01
870	CPD1250	N4 VV2	100mA, 200V Diode, FDH400	F	0.02
871	CPC1002	N4 WW1	330pF ±10%, 500V, Ceramic	F	0.01
872	CPR0011	M4 VV2	1.8KΩ ±5%, 1/4W, CF	F	0.01

Δ	Bd.#	Part No.	Bd.	Sch. Ref.	Description	PAD	Price
	873	CPR0370	M4	WW1	10KΩ ±5%, 1/2W, CF	F	0.01
	874	CPR0011	M4	VV1	1.8KΩ ±5%, 1/4W, CF	F	0.01
	875	CPR0351	L4	YY2	150Ω ±10%, 1/2W, CC	F	0.06
	876	CPR0019	L4	VV1	100KΩ ±5%, 1/4W, CF	F	0.01
!	877	CPS1850	L3	XX0	Dual Focus CRT Socket	F	1.31
	878	CPC1003	L3	XX1	2,200pF ±20%, 1KV, Ceramic	F	0.02
	879	CPR0002	L3	XX2	18Ω ±5%, 1/4W, CF	F	0.01
	880	CPR0351	L3	YY1	150Ω ±10%, 1/2W, CC	F	0.06
	881	CPR0368	M3	YY1	2.2KΩ ±5%, 1/2W, CF	F	0.01
	882	CPR0351	L3	XX1	150Ω ±10%, 1/2W, CC	F	0.06
	883	CPR0365	L2	WW1	470Ω ±5%, 1/2W, CF	F	0.01
	884	CPR0012	K2	VV6	2.7KΩ ±5%, 1/4W, CF	F	0.01
	885	CPC1040	K3	SS6	.015uF ±10%, 250V, Film	F	0.06
	886	CPD1250	K3	VV0	100mA, 200V Diode, FDH400	F	0.02
	887	CPC1037	K2	TT6	.1uF ±5%, 250V, Film	F	0.07
	888	CPD1251	K2	VV6	10mA, 75V Diode, 1N4148	F	0.01
	889	CPC1003	L2	WW6	2,200pF ±20%, 1KV, Ceramic	F	0.02
	890	CPR0009	K2	WW7	1KΩ ±5%, 1/4W, CF	F	0.01
	891	CPR0015	K2	VV6	22KΩ ±5%, 1/4W, CF	F	0.01
	892	CPC1101	L2	YY5	10uF, 50V, Electrolytic	F	0.03
	893	CPR0050	L2	J	0Ω, Jumper Wire	F	0.01
	894	CPC1101	L2	YY5	10uF, 50V, Electrolytic	F	0.03
	895	CPC1101	L2	YY4	10uF, 50V, Electrolytic	F	0.03
	899	CPD1250	N3	UU0	100mA, 200V Diode, FDH400	F	0.02
	900	CPR0365	N3	WW0	470Ω ±5%, 1/2W, CF	F	0.01
	901	CPC1040	N2	SS1	.015uF ±10%, 250V, Film	F	0.06
	902	CPR0050	N2	J	0Ω, Jumper Wire	F	0.01
	903	CPD1252	N2	VV3	1A, 1KV Diode, 1N4007	F	0.01
	904	CPR0050	M2	J	0Ω, Jumper Wire	F	0.01
	905	CPD1252	M2	WW3	1A, 1KV Diode, 1N4007	F	0.01
	906	CPD1252	M2	WW3	1A, 1KV Diode, 1N4007	F	0.01
	907	CPC1058	M2	WW4	.1uF ±5%, 50V, Film	F	0.05
	908	CPR0016	M2	YY4	33KΩ ±5%, 1/4W, CF	F	0.01
	909	CPR0024	M1	ZZ4	3.3KΩ ±5%, 1/4W, CF	F	0.01
	910	CPR0016	M2	YY5	33KΩ ±5%, 1/4W, CF	F	0.01
	911	CPR0016	M2	YY5	33KΩ ±5%, 1/4W, CF	F	0.01
	912	CPR0018	M2	ZZ4	62KΩ ±5%, 1/4W, CF	F	0.01
	913	CPC1037	N2	TT0	.1uF ±5%, 250V, Film	F	0.07
	914	CPR0145	N1	ZZ4	15.8KΩ ±1%, 1/4W, MF	F	0.01
	915	CPR0050	N1	J	0Ω, Jumper Wire	F	0.01
	917	CPR0506	M1	WW4	"C" PRA, CRT Auto Bias	F	0.79
	918	CPR0050	M1	J	0Ω, Jumper Wire	F	0.01
	920	CPI1405	M1	WW4	Quad OP Amp IC, LM324	F	0.24
	921	CPC1058	M1	WW4	.1uF ±5%, 50V, Film	F	0.05
	922	CPC1036	M1	WW4	.047uF ±5%, 50V, Film	F	0.04
	923	CPC1058	L1	WW5	.1uF ±5%, 50V, Film	F	0.05
	924	CPC1036	L1	WW5	.047uF ±5%, 50V, Film	F	0.04
	925	CPC1058	L1	WW5	.1uF ±5%, 50V, Film	F	0.05
	926	CPC1036	L1	WW6	.047uF ±5%, 50V, Film	F	0.04
	927	CPI1402	L2	XX4	CRT Bias IC, CA3224E	F	3.47
	928	CPQ1301	K1	WW7	60V, .6A, PNP, PN2907A	F	0.04
	930	CPC1058	K1	VV7	.1uF ±5%, 50V, Film	F	0.05
	931	CPR0011	K1	WW7	1.8KΩ ±5%, 1/4W, CF	F	0.01
	932	CPR0050	L1	J	0Ω, Jumper Wire	F	0.01
	933	CPR0011	K1	WW7	1.8KΩ ±5%, 1/4W, CF	F	0.01
	934	CPC1058	K1	RR7	.1uF ±5%, 50V, Film	F	0.05
	935	CPR0050	L1	J	0Ω, Jumper Wire	F	0.01
	936	CPR0050	K1	J	0Ω, Jumper Wire	F	0.01
	937	CPR0511	K1	RR5	"Blue" PRA Video Amplifier	F	1.02
	938	CPR0011	K1	VV7	1.8KΩ ±5%, 1/4W, CF	F	0.01
	940	CPR0140	K1	VV7	3.92KΩ ±1%, 1/4W, MF	F	0.01
	941	CPC1003	K1	VV4	2,200pF ±20%, 1KV, Ceramic	F	0.02

Δ	Bd.#	Part No.	Bd.	Sch. Ref.	Description	PAD	Price
	942	CPQ1302	K1	VV7	30V, .3A, PNP, D, MPSA64	F	0.06
	943	CPQ1308	K2	SS7	.1A, 200V, NPN, 2SC3467AE	F	0.18
	944	CPR0050	K2	J	0Ω, Jumper Wire	F	0.01
	945	CPQ1301	K2	SS7	60V, .6A, PNP, PN2907A	F	0.04
	946	CPR0050	K2	J	0Ω, Jumper Wire	F	0.01
	947	CPR0050	K2	J	0Ω, Jumper Wire	F	0.01
	948	CPR0011	K2	TT7	1.8KΩ ±5%, 1/4W, CF	F	0.01
	950	CPQ1301	K2	SS5	60V, .6A, PNP, PN2907A	F	0.04
	951	CPQ1309	K2	SS6	.1A, 200V, PNP, 2SA1370AE	F	0.23
	952	CPR0050	K2	J	0Ω, Jumper Wire	F	0.01
	953	CPR0127	K2	SS6	205Ω ±1%, 1/4W, MF	F	0.01
	954	CPQ1309	K3	TT7	.1A, 200V, PNP, 2SA1370AE	F	0.23
	955	CPR0011	K3	TT7	1.8KΩ ±5%, 1/4W, CF	F	0.01
	956	CPC1005	K3	TT6	1,000pF ±10%, 500V, Ceramic	F	0.01
	957	CPC1058	K3	TT5	.1uF ±5%, 50V, Film	F	0.05
	958	CPD1250	K3	TT7	100mA, 200V Diode, FDH400	F	0.02
	959	CPD1250	K4	WW0	100mA, 200V Diode, FDH400	F	0.02
	961	CPS1758	K4	YY1	.093" Bead Pin, Dag. GND	F	0.02
		CPM2043			Video Board Cover	F	0.61
!	CRT	CPP1726		17"	Chunghwa M41AGE13X47R CRT.	F	140.0
		CPS1831			17" Grounding Strap	F	0.33
ID		Solder Conn.	E6	KK4	Horizontal Frequency Adj.	F	
M		CPM2024			Front Support Bracket	F	1.87
M		CPM2026			Right Support Bracket	F	0.42
M		CPM2029			Left Support Bracket	F	0.42
M		CPM2060			Rear Support Bracket	F	0.26
M		CPM2113	G6		H. Transistor Support	F	
M		CPM2550	G6		H. Transistor Support Screw	F	
M		CPM2551	G6		H. Transistor Support Screw	F	0.03
S2		Solder Conn.	F5	PP3	Raster Shift, Two Units.	F	
SR		Solder Conn.	G5	OO3	Raster Shift Right.	F	
V+		70.0			69.5V to 70.5V	F	