



Video PCB: CPA4248  
 FBT Screen Voltage: 453  
 4.0V to 4.4 V measured at 920 Pin 8.

NOTE: USE SUPPORT BRACKETS  
 CPM 2060 - (REAR)  
 CPM 2024 - (FRONT)  
 CPM 2026 - (RIGHT)  
 CPM 2029 - (LEFT)

Video is: Positive analog. Black = 0.00V. Saturated Color = 0.70V  
 Sync is: Separate, -Horizontal and ±Vertical.  
 Solder connections are: ID, JD, U, SL & S4. I PRA (IB, IC, & ID) set for Hfo=37.9KHz ±400Hz  
 Vertical Frequency is 60Hz.

**CERONIX CPA4248** CRT: Samsung M41QCJ761X172  
**Model 1793-38DF** Power: 120VAC  
 Date: 05/31/02 Rev. E8